


CX40 Pro

LED Display Controller



Specifications



Change History

Document Version	Release Date	Description		
V1.5.0	2025-09-30	 Added support for 3D feature. HDMI 2.0 input supports YCbCr 4:2:0 color sampling 		
		format.		
		Supports Art-Net and central control protocol and viewing of device MAC address.		
		Supports SPDIF audio output.		
V1.4.0.B5	2024-07-26	• Supports importing 3D LUT files with an accuracy of 33x33x33 / 65x65x65.		
		Improved document information.		
V1.0.1	2023-07-04	Added descriptions for low latency.		
		Updated the supported driver ICs for frame rate adaptive.		
V1.0.0	2023-01-12	First release		

Introduction

The CX40 Pro is a 4K LED display controller in the brand-new control system COEX series of Xi'an NovaStar Tech Co., Ltd. (hereinafter referred to as NovaStar). This controller offers rich video input connectors (HDMI 2.0, DP 1.2 and 12G-SDI) and supports 5Gbps output via Ethernet port and 40Gbps remote transmission via optical port.

The CX40 Pro can also work with the brand-new software VMP (Vision Management Platform) to provide a better operation and control experience. Featuring a 5.5-inch touch LCD, it makes user operation and control much easier.

Certifications

CE, RoHS, FCC, IC, CCC, CB, UL

If the product does not have the relevant certifications required by the countries or regions where it is to be sold, please contact NovaStar to confirm or address the problem.

Otherwise, the customer shall be responsible for the legal risks caused or NovaStar has the right to claim compensation.



Features

Inputs and Outputs

- 3 types of inputs
 - 2x HDMI 2.0 (with loop through)
 - 1x DP 1.2
 - 2x 12G-SDI (with loop through)
- 12-bit, 10-bit and 8-bit video inputs
- 3 types of outputs
 - 6x 5Gbps Ethernet ports, load capacity up to 9 million pixels
 - 1x 40Gbps optical port
 - 1x SPDIF digital audio port
- 3 types of controls
 - 1x Genlock signal input (with loop through)
 - 2x Ethernet control ports
 - 1x Auxiliary port

Advanced Functions

• 3 independent layers

Support up to 3x 4K layers and layer priority adjustment in Z order.

• Image Scaling

Each layer supports 4 scaling mode: custom, pixel to pixel, snap to canvas, and fill screen.

• Color Replacement

Replace any color in the image with another color without affecting other colors. It is recommended to choose color with higher saturation for replacement to achieve better outcome.

• 14Ch Color Correction

Supports precise adjustment to the hue, saturation, and brightness of black and white, and the 12 standard colors derived from the three primary colors (RGB).

Color Curves



Supports adjustment to the RGBW mapping curves of the screen.

3D LUT

Use the 3D LUT file (.cube) with an accuracy of 17×17×17 / 33×33×33 / 65×65×65 to adjust the colors of the video source.

• Dynamic Booster

Real-time analysis and dynamic adjustment are made to each frame to significantly improve the display contrast and image details for better visual experience, and effectively control and lower the display power consumption, extending the service life of the LED screen.

Full-Grayscale Calibration

Work with NovaStar's high-precision calibration system CC3 along with the scientific-grade cameras CC60 and C3200 to generate unique calibration coefficients for each grayscale, ensuring uniformity of each grayscale and dramatically improving the image quality.

HDR

- Support HDR10 and comply with the SMPTE ST 2084 and SMPTE ST 2086 standards.
- Support HLG.

• 3D

Work with the 3D emitter and 3D glasses to bring a fascinating and immersive 3D viewing experience.

Latency

- Different screens can have different latency settings. The minimum processing latency of the LED display controller is reduced to 0-frame (less than 1 ms), achieving low latency without reducing the load.
- Supports additional latency. Users can choose to add zero to two frames of latency.

Preset

For optimal display in various scenarios, users can adjust display parameters such as layers, brightness, color temperature, and gamma ahead of time and save them as presets. Users can save up to 128 customizable presets which can be easily applied or switched with just one click.

• No rectangle restriction

No rectangle restriction for irregular screens. This means when calculating resolutions, blank pixels do not count towards the total capacity. The used load capacity of Ethernet ports is the sum of the resolutions of all cabinets with load.

• Frame Rate Adaptive



Automatically adapt to video inputs with different frame rates ranging from 23.98 Hz to 480 Hz, and support the automatic calculation of optimal screen parameters based on the input source's frame rate. This ensures that the brightness deviation of the screen remains within 5% across different frame rates. It also supports precise frame rate adjustment in 0.01 Hz increments.

Two working modes

Support the All-In-One Controller and Send-Only Controller working modes.

- In the Send-Only Controller mode, the latency can be reduced by one frame.
- In the All-In-One Controller mode, the layer and scaling functions are available.

Shutter Fit

Automatically adjusts the driver IC parameters according to the camera shutter angle to fix problems of black lines, grayscale addition, and grayscale loss during camera shooting in xR scenarios.

Frame Multiplication

- Frame interpolation: Outputs images that are captured from multiple shooting angles with different backgrounds at the same time. Solid green backgrounds can also be inserted to allow for easy post-production adjustments.
- Frequency multiplication: Supports high frame rates of up to 480 Hz. This feature is to accommodate multi-angle camera shooting to improve the screen performance under the camera.

Device Controls

LCD touch panel

Equipped with a -inch touch screen, which is responsive, sturdy and durable. Users can easily give commands with a gentle touch, making the operation effortless.

VMP software control

The device can be connected to the VMP software to provide easy and convenient operations and smart device management.

- Supports the SNMP, Art-Net, and central control protocols.
- Cascading control via Ethernet

The Gigabit Ethernet control ports support TCP/IP protocol and star topology. No switch or router is needed to deploy multiple devices on the same LAN via device cascading as the network switching function is already built in.



• Automated system monitoring and alarm

Hardware monitoring capabilities that encompass fan speed, module temperatures, voltage levels, and operational status. It automatically detects and reports any device faults or alarm information, ensuring real-time monitoring of the LED screen's operational status.

Table 4-1 Function Limitations

Function	Limitation
Frame Rate Adaptive	To use this function, it is required to pair with the XA50 Pro or CA50E receiving cards and specific driver ICs (for detailed IC models, please see the product specifications on the NovaStar website at https://www.novastar.tech/). Additionally, you must use the Cabinet Tool provided by NovaStar to adjust the driver IC parameters for different frame rates, which will generate the required NCP file.
Dynamic Booster	It is required to work with the XA50 Pro or CA50E receiving cards. Users need to use a CA410-VP427, CA410-P427, or CA410-P427H colorimeter to perform the gamut and brightness correction.
Full Grayscale Calibration	It is required to work with the XA50 Pro or CA50E receiving cards and users need to use a CC60\C3200 camera to perform the full-grayscale calibration.
Calibration Software	COEX V1.5.0 and later versions no longer support the Calcube2.X. Please use the official version of the CC3 calibration software for calibration.
Low Latency	Low Latency cannot be enabled simultaneously with Genlock. Moreover, it is recommended to ensure all Ethernet ports load the cabinets vertically and share the same Y coordinate (all set to 0) when Low Latency is enabled.
3D	3D cannot be enabled simultaneously with Low Latency and Frame Multiplication. To use the 3D function, specified 3D glasses are needed. For details, please contact NovaStar technical support.
HDR	Supports both automatic parsing and manual settings for HDR. When the input interfaces are HDMI 2.0, HDR10 and HLG are supported. For 12G-SDI, DP 1.2, and non-standard HDR sources, HDR attributes can only be manually overridden.

Table 4-2 Supported Receiving Card Models

Receiving Card Model	Supported		
CA50E	Only V1.3.0.0 or later is supported.		
XA50 Pro	Yes		



Appearance

Front Panel



Name	Function
Running	Solid red: Standby.
indicator	Solid blue: The device is being powered on.
	Solid green: The device is running normally.
	Flashing red: The device is running abnormally.
Standby	Press the button to power on or power off the device.
button	Hold down the button for 5s to 10s to restart the device.
USB 2.0	Connect to a USB drive only to export the device diagnostic result.
	Only the NTFS and FAT32 file systems are supported. Others are not supported.
IPS touchscreen	A 5.5-inch screen that is for displaying the device status, settings, and sending commands.
Knob	On the home screen, press the knob to enter the main menu screen.
	On the main menu screen, rotate the knob to select a menu item or adjust the parameter value. Press the knob to confirm the operation.
	Hold down the knob and BACK button simultaneously for 5s or longer to lock or unlock the buttons and screen.
BACK	Go back to the previous menu or cancel the current operation.



Rear Panel



Inputs						
Туре	Qty	Description				
HDMI 2.0-1 IN	1	Resolutions	Max resolution: 4096×2160@60Hz/8192×1080@60Hz (Forced) Min resolution: 800×600@60Hz			
		Max width/height (Forced)	Max width: 8192 pixels (8192×1080@60Hz) Max height: 8192 pixels (1080×8192@60Hz)			
		Frame rates	23.98/24/25/29.97/30/47.95/48/50/59.94/60/71.93/72/75 /100/119.88/120/143.86/144/240 Hz			
		HDR	Support HDR10 and comply with the SMPTE ST 2084 and SMPTE ST 2086 standards. Support HLG.			
		EDID management	Support standard resolutions, up to 3840×2160@60Hz. Support custom input resolutions.			
		HDCP	HDCP 2.2 compliant, backwards compatible with HDCP 1.4/HDCP 1.3.			
		Interlaced signal inputs	Not supported.			
HDMI 2.0-2 IN	1	Resolutions	Max resolution: 4096×2160@60Hz/8192×1080@60Hz (Forced) Min resolution: 800×600@60Hz			
		Max width/height (Forced)	Max width: 8192 pixels (8192×1080@60Hz) Max height: 7680 pixels (1080×7680@60Hz)			
		Frame rates	23.98/24/25/29.97/30/47.95/48/50/59.94/60/71.93/72/75 /100/119.88/120/143.86/144/240 Hz			
		HDR	Support HDR10 and comply with the SMPTE ST 2084 and			



Inputs					
Туре	Qty	Description			
			SMPTE ST 2086 standards. Support HLG.		
		EDID management	Support standard resolutions, up to 3840×2160@60Hz. Support custom input resolutions.		
		HDCP	HDCP 2.2 compliant, backwards compatible with HDCP 1.4/HDCP 1.3.		
		Interlaced signal inputs	Not supported.		
DP 1.2	1	Resolutions	Max resolution: 4096×2160@60Hz/8192×1080@60Hz (Forced)		
			Min resolution: 800×600@60Hz		
		Max width/height (Forced)	Max width: 8192 pixels (8192×1080@60Hz) Max height: 8192 pixels (1080×8192@60Hz)		
		Frame rates	23.98/24/25/29.97/30/47.95/48/50/59.94/60/71.93/72/75 /100/119.88/120/143.86/144/240 Hz		
		EDID management	Support standard resolutions, up to 3840×2160@60Hz. Support custom input resolutions.		
		HDCP	HDCP 1.3 compliant.		
		Interlaced signal inputs	Not supported.		
12G-SDI IN	2	Standards	Support ST-2082 (12G), ST-2081 (6G), ST-424 (3G) and ST-292 (HD) standard video inputs. Support 3G-Level A.		
		Resolution	Max resolution: 4096×2160@60Hz Min resolution: 720×480i@59.94Hz		
		Frame rates	23.98/24/25/29.97/30/47.95/48/50/59.94/60 Hz		
		Interlaced signal inputs	Support interlaced signal inputs, including 1080i/576i/480i.		
		Cables	Recommend using the CANARE-12G SDI coaxial cable. Cables up to 50 meters are supported.		



Inputs			
Туре	Qty	Description	
Туре	Qty	Description	
5GBASE- T×6	6	 5Gbps Ethernet ports. Max device load capacity: 9 million pixels Max output width/height: 16,384 pixels The maximum load capacity per port is as follows. For details, please refer to Ethernet Port Load Capacity 8bit@60Hz: 2,951,200 pixels 10bit@60Hz: 2,213,200 pixels 12bit@60Hz: 1,475,600 pixels The load capacity of a single Ethernet port can only achieve its maximum when the load width is 128 pixels or more. If the load width is less than that, the load capacity will be reduced accordingly, calculated as (128 - load width) × load height. 	
40G QSFP+	1	40Gbps optical port with a transmission rate of 41.25 Gbps. Note The product doesn't include an optical module by default. If you need one, it's recommended to choose a compatible NovaStar product.	
HDMI 2.0 LOOP	2	HDMI loop through. Up to 8 devices can be cabled in one loop.	
12G-SDI LOOP	2	SDI loop through. Up to 8 devices can be cabled in one loop.	
SPDIF OUT	1	Digital audio output connector allows for using the HDMI 2.0_2 input source as the audio output.	
Controls	1		
Туре	Qty	Description	
ETHERNET	2	Gigabit Ethernet control ports. Support TCP/IP protocol and star connection. They have the same functions without priority and order, and can be connected to VMP software and central control devices. No switch or router is needed to deploy multiple devices on the same LAN via device cascading as the network switching function is already built in. Up to 20 CX40 Pro can be cascaded.	




Inputs	Inputs				
Туре	Qty	Description			
GENLOCK	1	A pair of Genlock signal connectors. Support Bi-Level, Tri-Level, and Blackburst. IN: Accept the sync signal LOOP: Loop the sync signal The Genlock input signal supports a frame rate range from 23.98 Hz to 60 Hz. For standard Genlock signal generators, up to 20 CX40 Pro can be cascaded.			
AUX	1	An auxiliary connector for connecting to central control devices (RS232).			
Power					
100-240V~, 50/60Hz	1	An AC power input connector and switch.			



The maximum input resolution and maximum width and height of HDMI and DP connectors must be obtained by setting the graphics card.



Dimensions



Tolerance: ±0.3 [±0.012] Unit: mm [inch]

Product Specifications

Electrical	Power supply	100-240V~, 50/60Hz		
Specifications	Power consumption	105 W		
Operating	Temperature	-20°C to +45°C		
Environment	Humidity	0% RH to 80% RH, non-condensing		
Storage	Temperature	-30°C to +80°C		
Environment	Humidity	0% RH to 95% RH, non-condensing		
Physical	Dimensions	482.6 mm × 94.4 mm × 472.0 mm		
Specifications	Net weight	8.1 kg		
	Gross weight	11.1 kg		
		Note: It is the total weight of the product, accessories, and		



		packing materials packed according to the packing specifications.		
Packing	Packing box	595.0 mm × 575.0 mm × 215.0 mm, kraft paper box		
Information	Accessory box	408.0 mm × 294.0 mm × 51.0 mm, white cardboard box		
	Accessories	• 1x Power cord		
		• 1x Ethernet cable		
		• 1x HDMI cable		
		• 1x DP cable		
		1x Certificate of Approval		
IP Rating		IP20 (Please prevent the product from water intrusion and do not wet or wash the product).		
Noise Level (typical at 25°C/77°F)		45 dB (A)		

The amount of power consumption may vary depending on various factors such as product settings, usage, and environment.

Video Source Specifications

Input	Resolution		Color Space	Sampling	Bit Depth	Integer Frame Rate (Hz)
HDMI	4K	4096×2160 RGB	RGB /	4:4:4	12bit	24/25/30
2.0		(Forced)	YCbCr		10bit	24/25/30/48/50
					8bit	24/25/30/48/50/60
			YCbCr	4:2:2	8/10/12bit	
				4:2:0	8/10/12bit	30/48/50/60
		-	4:4:4	12bit	24/25/30	
			YCbCr	Cr	10bit	24/25/30/48/50
					8bit	24/25/30/48/50/60
			YCbCr	4:2:2	8/10/12bit	
				4:2:0	8/10/12bit	48/50/60
	2K1K 256	K 2560×1440 RGB /	B / 4:4:4	12bit	24/25/30/48/50/60/75	
			YCbCr		10bit	24/25/30/48/50/60/75/100
					8bit	24/25/30/48/50/60/75/100/120



Input	Resolu	tion	Color Space	Sampling	Bit Depth	Integer Frame Rate (Hz)
			YCbCr	4:2:2	8/10/12bit	
				4:2:0	8/10/12bit	75/100/120
		1920×1080	RGB /	4:4:4	12bit	24/25/30/48/50/60/72/75/100/120/144
			YCbCr		10bit	
					8bit	24/25/30/48/50/60/72/75/100/120/144/240
			YCbCr	4:2:2	8/10/12bit	
				4:2:0	8/10/12bit	120/144/240
DP 1.2	4K	4096×2160	RGB/	4:4:4	12bit	24/25/30/48/50
		(Forced)	YCbCr		10bit	24/25/30/48/50/60
					8bit	24/25/30/48/50/60/75
			YCbCr	4:2:2	8/10/12bit	
		3840×2160	RGB / YCbCr	4:4:4	12bit	24/25/30/48/50
					10bit	24/25/30/48/50/60
					8bit	24/25/30/48/50/60/75
			YCbCr	4:2:2	8/10/12bit	(75 Hz needs to be forced)
	2K1K	2560×1440	RGB / YCbCr	4:4:4	12bit	24/25/30/48/50/60/75/100
					10bit	24/25/30/48/50/60/75/100/120
					8bit	24/25/30/48/50/60/75/100/120/144 (144
			YCbCr	4:2:2	8/10/12bit	Hz needs to be forced)
		1920×1080	RGB / YCbCr	4:4:4	12bit	24/25/30/48/50/60/75/100/120/144 (144
					10bit	Hz needs to be forced)
					8bit	24/25/30/48/50/60/75/100/120/144/240 (240 Hz needs to be forced)
			YCbCr	4:2:2	8/10/12bit	(240 Hz fleeds to be forced)
12G- SDI	4K	4096×2160	YCbCr	4:2:2	10bit	24/25/30/48/50/60
		3840×2160				
	2K1K	2048×1080				
		1920×1080				





- The table above only displays a selection of common resolutions and integer frame rates.
 Decimal frame rates are also supported, allowing for automatic frame rate adaptation from the highest frame rate of each resolution down to 23.98/29.97/47.95/59.94/71.93/119.88/143.86
 Hz.
- When using YCbCr 4:2:0 input, all frame rates need to be forced. Standard graphics cards only support a 4K resolution at 50/60 Hz. Other resolutions and frame rates require a source device that supports this color space and sampling to be forced.

Ethernet Port Load Capacity

When working with the XA50 Pro and CA50E receiving cards, the formula of calculating the load capacity per Ethernet port and the detailed parameters are as follows:

- 8bit: Load capacity × 24 × Frame rate < 5G × 0.85
- 10bit: Load capacity × 32 × Frame rate < 5G × 0.88
- 12bit: Load capacity × 48 × Frame rate < 5G × 0.85

Max Load Capacity per Ethernet Port (Pixels)			
Frame Rate / Bit Depth	8bit	10bit	12bit
24 Hz	7,378,000	5,728,280	3,689,000
25 Hz	7,082,800	5,499,149	3,541,440
30 Hz	5,902,400	4,582,624	2,951,200
50 Hz	3,541,440	2,749,574	1,770,720
60 Hz	2,951,200	2,291,312	1,475,600
120 Hz	1,475,600	1,145,656	737,800
144 Hz	1,229,600	954,713	612,374
240 Hz	737,800	572,828	368,900



The load capacity of a single Ethernet port can only achieve its maximum when the load width is 128 pixels or more. If the load width is less than that, the load capacity will be reduced accordingly, calculated as (128 - load width) × load height.




Notes and Cautions

Notes for Battery

- The battery is not intended to be replaced.
- Disposal of a battery into fire or a hot oven, or mechanically crushing or cutting of a battery can result in an explosion.
- Leaving a battery in an extremely high temperature surrounding environment can result in an explosion or the leakage of flammable liquid or gas.
- A battery subjected to extremely low air pressure may result in an explosion or the leakage of flammable liquid or gas.

Notes for Installation

When the product needs to be installed on the rack, 4 screws at least M5*12 should be used to fix it. The rack for installation shall bear at least 9kg weight.



- Elevated Operating Ambient If installed in a closed or multi-unit rack assembly, the
 operating ambient temperature of the rack environment may be greater than room ambient.
 Therefore, consideration should be given to installing the equipment in an environment
 compatible with the maximum ambient temperature (Tma) specified by the manufacturer.
- Reduced Air Flow Installation of the equipment in a rack should be such that the amount of air flow required for safe operation of the equipment is not compromised.
- Mechanical Loading Mounting of the equipment in the rack should be such that a hazardous condition is not achieved due to uneven mechanical loading.
- Circuit Overloading Consideration should be given to the connection of the equipment to the supply circuit and the effect that overloading of the circuits might have on overcurrent



- protection and supply wiring. Appropriate consideration of equipment nameplate ratings should be used when addressing this concern.
- Reliable Earthing Reliable earthing of rack-mounted equipment should be maintained.
 Particular attention should be given to supply connections other than direct connections to the branch circuit (e.g. use of power strips).

FCC Caution

- Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.
- This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.
- Note: This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

Others

- This product can only be placed horizontally. Do not mount vertically or upside-down.
- This is Class A product. In a domestic environment, this product may cause radio interference in which case the user may be required to take adequate measures.



Copyright

Copyright © 2025 Xi'an NovaStar Tech Co., Ltd. All Rights Reserved.

No part of this document may be copied, reproduced, extracted or transmitted in any form or by any means without the prior written consent of Xi'an NovaStar Tech Co., Ltd.

Trademark

NOVA 5TAR is a trademark of Xi'an NovaStar Tech Co., Ltd.

Statement

Thank you for choosing NovaStar's product. This document is intended to help you understand and use the product. For accuracy and reliability, NovaStar may make improvements and/or changes to this document at any time and without notice. If you experience any problems in use or have any suggestions, please contact us via the contact information given in this document. We will do our best to solve any issues, as well as evaluate and implement any suggestions.

Official website www.novastar.tech Technical support support@novastar.tech